



UK sockets shown for illustration purposes.

### Connecting to power

#### Connecting standard 3-pole connector




Plug the male 3-pole connector supplied as standard into a female powered connector.




Ensure the attached locking mechanism clicks into place on both connectors.

#### Disconnecting standard 3-pole connector




Use a suitable tool to release the locking mechanism.




Separate the connectors.


### Contents



### Mounting to desk




Lower the Porthole into a Ø80mm hole in the desk. Feed the cable through the fixing nut.




Ensure the socket is in the desired orientation and secure in place by tightening fixing nut.

### Connecting data/AV (if applicable)


#### Porthole power and data model only




Separate the outer housing from the power module.



Depress the clip on the keystone blank and pull away from the module.





Remove the keystone blank.



Insert data keystone then re-insert module into housing.

### USB Charging (if applicable)



### Additional information

#### Safety

- Installation is to be carried out in accordance with relevant Health & Safety regulations and only to be carried out by a skilled or competent person.
- The product should be installed to comply with the relevant national standards and be inspected and tested prior to being put into service (in the UK BS 7671 Wiring Regulations or BS 6396 Office and Educational Systems Best Practice).
- Isolate the supply before installation or repositioning. Any locking mechanisms must be used and fully engaged.
- Incorrect use could lead to risk of electrocution.
- Connectors must not be engaged or disengaged when under load or live.
- Product to be used only for the intended purpose of distributing power and data in office and commercial environments.
- Do not misuse, dismantle or re-configure the product because doing so will invalidate the warranty.

#### Standards

- Refer to the Declaration of Conformity.

#### Further guidance

- Fuse replacement only to be carried out by a skilled or competent person.
- Should the supply cable need replacing, contact CMD.

#### Product care

- Clean using a dry cloth. No abrasives or solvents to be used on the product.
- Do not drop or expose to moisture.